

Brother DCP 8060: Laser Printer, Scanner, & Copier



Installing the Scanner:

You will need to complete two installation steps prior to being able to use the scanner and the offline test features (plain-paper testing) of the **Houghton Mifflin Online Assessment System**:

1. Use the installation CD that comes with the scanner to load the scanner drivers onto the PC.
 - a. Follow the instructions that are included with the CD.
 - b. After completing this step, you will be able to use the Brother DCP 8060 as a stand-alone piece of equipment. However, without completing the second installation step, the **Houghton Mifflin Online Assessment System** will not allow any functionality for the offline test features.

Note: The scanner must be connected to a PC (not a Mac) that is also connected to the Internet.

2. Download and install the scanning software from the **Houghton Mifflin Online Assessment System** website.
 - a. In order to access the download, you will need to have activated the license and claimed the product from an active, shipped order.
 - b. Once the Administrator has registered as a User, they will be able to access the scanning software download from a link on their **Houghton Mifflin Online Assessment System** homepage.
 - c. Follow the directions provided in the online help documentation in order to install the scanning software.

Note: Both of these steps should only take a minimal amount of time to complete.

Technical Specifications

Printer	
Print Technology	B/W Laser Technology
Max. Black Print Speed	30ppm Black
Print Resolution (maximum dpi)	Up to 1200x1200 dpi
Duplex Printing Standard	No
Standard Input Paper Capacity (sheets)‡	250-Sheet Input Capacity
Optional Paper Capacity (sheets)‡	LT-5300 (250 sheets)
Multi-purpose Tray Capacity‡	50-Sheet Multi-Purpose Tray Capacity
Standard Interface(s)	Parallel and High Speed USB 2.0 Interfaces
Optional Interface(s)	No
Printer Driver Compatibility†	Windows® and Mac OS®
Emulation(s)	PCL6 & BR-Script 3‡
Secure Printing	Yes
Max Monthly Duty Cycle	20,000 printed pages
First Time to Print	Approx. 8.5 seconds or less
Standard Memory (MB)	32MB Memory
Optional Memory (MB)	Yes (up to 544MB)‡



Copier	
Design Style	Flatbed
Color/B&W Copying	B/W Copying
Max Copy Speed B/W (cpm) / Resolution	30cpm Black
Reduction/Enlargement	25%–400%
Document Glass Size	Legal-size
Stand-alone Copying	No PC Required
Sorting Function	Yes
N in 1 Function	2in1/4in1
Poster Function	Yes
Scanner	
Color/B&W Scanning	B/W & Color Scanning
Interpolated Scan Resolution (dpi)	19,200x19,200 dpi
Optical Scan Resolution (dpi)	600x2400 dpi
Color Scan Bit Depth	48-bit
Scanner Driver Compatibility	Windows®/Mac OS®
Document Viewer Software	Includes Scansoft PaperPort® SE with OCR for Windows® and Presto!® PageManager® for Mac®
OCR Software	Includes Scansoft PaperPort® SE with OCR for Windows® and Presto!® PageManager® for Mac®
Other	
(Plain/Inkjet/Glossy/Trans)	Plain Paper: Xerox 4200DP 20 lb., Hammermill Laser Paper 24 lb. Recycled Paper: Xerox Recycled Supreme Transparency: 3M CG 3300 Labels: Avery Laser Label #5160
Toner Save Mode	Yes
Output Paper Capacity (sheets)	150 sheets
Sheet Weight–Paper tray (max/min)	16–28 lbs.
Power Consumption–Sleep/Standby/Peak	15W/85W/1092W
Energy Star Compliant	Yes
Carton Dimensions (W"xD"xH")	24.7" x 22.3" x 22.6"
Unit Dimensions (W"xD"xH")	20.9" x 17.7" x 18.7"
Carton Weight (lbs.)	48.0 lbs.
"In-Box" Consumables (Yield)‡	(1) TN550 Standard Yield Toner Cartridge (3,500 pages) (1) DR520 Drum Unit (25,000 pages)
Unit Weight (lbs.)	35.4 lbs.
Max Paper Width/Length (Paper Tray)	8.5"/14"
UPC Code	0 12502 61506 4
Warranty‡	3 Year Warranty: 2 Year Exchange/1 Year Depot